

# ORIGINAL - PSX

OSRAM spare parts



## OSRAM spare parts

Discover our ORIGINAL PSX lamps. The spare parts are signal lamp types for different applications. They provide a high and constant luminous flux.

Product family datasheet

Technical data

| Product description   | Product information                         | General Product Information | Electrical Data |                 |                 |
|-----------------------|---------------------------------------------|-----------------------------|-----------------|-----------------|-----------------|
|                       | Application (Category and Product specific) | Global order reference      | Power input     | Nominal voltage | Nominal wattage |
| ORIGINAL - PSX PS19W  | Auxiliary lamp                              | 5201                        | 20 W            | 12 V            | 19 W            |
| ORIGINAL - PSX PS24W  | Auxiliary lamp                              | 5202                        | 25 W            | 12 V            | 24 W            |
| ORIGINAL - PSX PSX24W | Auxiliary lamp                              | 2504                        | 25 W            | 12 V            | 24 W            |
| ORIGINAL - PSX PSX26W | Auxiliary lamp                              | 6851                        | 26 W            | 12 V            | 24 W            |
| ORIGINAL - PSX P13W   |                                             | 828                         | 13 W            | 12 V            | 13 W            |
| ORIGINAL - PSX PW24W  |                                             | 7447                        | 25 W            | 12 V            | 24 W            |
| ORIGINAL - PSX PWY24W |                                             | 7450A                       | 25 W            | 12 V            | 24 W            |
| ORIGINAL - PSX PY24W  |                                             | 5200A                       | 25 W            | 12 V            | 24 W            |
| ORIGINAL - PSX PSY24W |                                             | 2503A                       | 25 W            | 12 V            | 24 W            |

| Product description   | Test voltage | Photometric Data      |                         | Physical Attributes & Dimensions |          |
|-----------------------|--------------|-----------------------|-------------------------|----------------------------------|----------|
|                       |              | Nominal luminous flux | Luminous flux tolerance | Diameter                         | Diameter |
| ORIGINAL - PSX PS19W  | 13.5 V       | 350 lm                | ±15 %                   | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PS24W  | 13.5 V       | 500 lm                | +10 %; -20 %            | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PSX24W | 13.5 V       | 500 lm                | +10 %; -15 %            | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PSX26W | 13.5 V       | 500 lm                | +10 %                   | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX P13W   | 13.5 V       | 250 lm                | +15% / -20 %            | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PW24W  | 13.5 V       | 500 lm                |                         | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PWY24W | 13.5 V       | 300 lm                |                         | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PY24W  | 13.5 V       | 300 lm                |                         | 18.5 mm                          | 18.5 mm  |
| ORIGINAL - PSX PSY24W | 13.5 V       | 300 lm                |                         | 18.5 mm                          | 18.5 mm  |

| Product description   | Lifetime Data |                | Capabilities      | Certificates & standards | Environmental & Regulatory Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH) |
|-----------------------|---------------|----------------|-------------------|--------------------------|--------------------------------------------------------------------------------------------------|
|                       | Lifespan B3   | Lifespan Tc    | Technology        | ECE category             | Primary article identifier                                                                       |
| ORIGINAL - PSX PS19W  | 500 hr        | 1000 hr        | AUX <sup>1)</sup> | PS19W                    | 4052899600546                                                                                    |
| ORIGINAL - PSX PS24W  | 500 hr        | 1000 hr        | AUX <sup>1)</sup> | PS24W                    | 4052899600584                                                                                    |
| ORIGINAL - PSX PSX24W | 500 hr        | 1000 hr        | AUX <sup>1)</sup> | PSX24W                   | 4052899600560                                                                                    |
| ORIGINAL - PSX PSX26W | 500 hr        | 1000 hr        | AUX <sup>1)</sup> | PSX26W                   | 4062172160100                                                                                    |
| ORIGINAL - PSX P13W   |               | 1500 h average | AUX <sup>1)</sup> | P13W                     | 4062172094283                                                                                    |
| ORIGINAL - PSX PW24W  |               | 500hr average  | AUX               | PW24W                    | 4062172406116                                                                                    |

Product family datasheet

|                       | Lifetime Data |               | Capabilities | Certificates & standards | Environmental & Regulatory Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH) |
|-----------------------|---------------|---------------|--------------|--------------------------|--------------------------------------------------------------------------------------------------|
| Product description   | Lifespan B3   | Lifespan Tc   | Technology   | ECE category             | Primary article identifier                                                                       |
| ORIGINAL - PSX PWY24W |               | 500hr average | AUX          | PWY24W                   | 4062172406147                                                                                    |
| ORIGINAL - PSX PY24W  |               | 500hr average | AUX          | PY24W                    | 4062172406178                                                                                    |
| ORIGINAL - PSX PSY24W |               | 500hr average | AUX          | PSY24W                   | 4062172406208                                                                                    |

| Product description   | Candidate list substance 1         | Declaration no. in SCIP database   |
|-----------------------|------------------------------------|------------------------------------|
| ORIGINAL - PSX PS19W  | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PS24W  | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PSX24W | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PSX26W | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX P13W   | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PW24W  | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PWY24W | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PY24W  | No declarable substances contained | No declarable substances contained |
| ORIGINAL - PSX PSY24W | No declarable substances contained | No declarable substances contained |

1) Auxiliary signal lamp

Download Data

| File                                                                              |                                                      |
|-----------------------------------------------------------------------------------|------------------------------------------------------|
|  | User instruction<br>GPRS_Safety symbols instructions |

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

